

WADE ANTENNA LTD.



MODEL LA58

Lightning Arrestors:

LA900
LA24
LA58

DESCRIPTION

This low loss lightning arrester is suited to provide protection from electrical surges. Only high quality connectors are used in the manufacturing of our lightning arrestors.

APPLICATION

Recommended for all outdoor antenna installations for surge protection.

SPECIFICATIONS

ELECTRICAL

| MODEL | LA900 | LA24 | LA58 |
|----------------|-----------------|------------------|------------------|
| FREQUENCY | 890 to 1250 MHz | 2100 to 2750 MHz | 5100 to 5850 MHz |
| IMPEDANCE | 50 Ohm | 50 Ohm | 50 Ohm |
| VSWR | 1.30:1 | 1.25:1 | 1.30:1 |
| TERMINAL TYPE | N FEMALE | N FEMALE | N FEMALE |
| INSERTION LOSS | 0.15 dB | 0.20 dB | 0.25 dB |

MECHANICAL

| | | | |
|--------|-------------------|-------------------|--------------------|
| SIZE | 1.5" x 3.5" | 1.5" x 2.5" | 1.5" x 2.0" |
| WEIGHT | 0.3 LBS (0.12 KG) | 0.2 LBS (0.08 KG) | 0.15 LBS (0.06 KG) |

Wade Antenna's ongoing policy of continuing development may result in specification changes to its products.