



MODEL LA-24

LIGHTNING ARRESTORS

- LA900
- LA-24
- LA-58

DESCRIPTION

This low loss lightning arrester is suited to provide protection from multiple electrical surges. Available for 900 MHz, 2.4 GHz or 5.8 GHz frequency bands.

APPLICATION

Recommended for all outdoor antenna installations. Unit may be installed outdoors.

SPECIFICATIONS

ELECTRICAL

MODEL	LA900	LA-24	LA-58
FREQUENCY	890 to 1250 MHz	2100 to 2750 MHz	5100 to 5850 MHz
IMPEDANCE	50 Ohm	50 Ohm	50 Ohm
VSWR	1.30:1	1.25:1	1.30:1
TERMINAL TYPE	N FEMALE	N FEMALE	N FEMALE
INSERTION LOSS	0.15 dB	0.20 dB	0.25 dB

MECHANICAL

MODEL	LA900	LA-24	LA-58
SIZE	1.5" x 3.5"	1.5" x 2.75"	1.5" x 2.25"
WEIGHT	0.3 LBS (0.12 KG)	0.32 LBS (0.15 KG)	0.26 LBS (0.12 KG)

WADE Antenna's ongoing policy of continuing development may result in specification changes to its products.

WADE Antenna Inc.

29 Sharp Road
 Brantford, Ontario, N3T 5L8 Canada
 Tel: 519.756.7157
 Fax: 519.756.5056

(800) 463-1607
sales@wadeantenna.com

www.wadeantenna.com